

# Formula and Reference Sheet

International System of Units (SI)

Prefix	Symbol		Value	
giga-	G	$10^9$	1,000,000,000	one billion
mega-	M	$10^6$	1,000,000	one million
kilo-	k	$10^3$	1,000	one thousand
(none)	(none)	$10^0$	1	one
centi-	c	$10^{-2}$	.01	one one-hundredth
milli-	m	$10^{-3}$	.001	one one-thousandth
micro-	$\mu$	$10^{-6}$	.000001	one one-millionth
nano-	n	$10^{-9}$	.000000001	one one-billionth
pico-	p	$10^{-12}$	.000000000001	one one-trillionth

## Technician Exam

Length of 1/2 wavelength antenna:

$$\text{Length (feet)} = \frac{468}{\text{Frequency (in MHz)}}$$

Length of 1/4 wavelength antenna:

$$\text{Length (feet)} = \frac{234}{\text{Frequency (MHz)}}$$

Ohm's law:

$$V = I * R, \quad I = \frac{V}{R}, \quad R = \frac{V}{I}$$

where:

*V is the voltage in Volts (V), I is the current in Amps (A), R is the resistance in Ohms ( $\Omega$ )*

Power formulas:

$$P = V * I, \quad I = \frac{P}{V}, \quad V = \frac{P}{I}$$

where:

*P is the power in Watts (W), V is the voltage in Volts (V), I is the current in Amps (A)*

## General Exam

Standing wave ratio:

$$SWR = \frac{\text{highest impedance}}{\text{lowest impedance}}$$

Equal-value resistors in series:      Equal-value resistors in parallel:      Resistors in parallel:

$$R_t = \frac{R_i}{n}$$

$$R_t = \frac{R_i}{n}$$

$$\frac{1}{R_t} = \frac{1}{R_1} + \frac{1}{R_2} + \frac{1}{R_3}$$

Inductors in series:

Equal-value inductors in parallel:

$$L_t = L_1 + L_2$$

$$L_t = \frac{L_i}{n}$$

Capacitors in series:

Equal-value capacitors in series:

Capacitors in parallel:

$$\frac{1}{C_t} = \frac{1}{C_1} + \frac{1}{C_2} + \frac{1}{C_3}$$

$$C_t = \frac{C_i}{n}$$

$$C_t = C_1 + C_2 + C_3$$

Transformers:

$$E_s = E_p * \left( \frac{N_s}{N_p} \right) \quad \frac{N_p}{N_s} = \sqrt{\frac{Z_p}{Z_s}}$$

RMS voltage:

$$V_p = \frac{V_{RMS}}{0.707}, \quad V_{RMS} = V_p * 0.707$$

$$V_{pp} = V_p * 2$$

Power:

$$P = E * I \quad P = \frac{E^2}{R} \quad P = I^2 * R \quad E = \sqrt{P * R}$$

Peak envelope power:

$$PEP = \frac{V_{RMS}^2}{R}$$

Decibel math:

$$\text{loss factor} = 10^{\left( \frac{-\text{loss(in db)}}{10} \right)} \quad \text{percent loss} = (1 - \text{loss factor}) * 100$$

Frequency modulation:

$$\text{bandwidth} = 2 * (D_{MAX} + M_{MAX})$$

Upconverter:

$$\text{multiplier} = \frac{\text{transmitted frequency}}{\text{lower frequency}}$$

$$\text{lower frequency maximum deviation} = \frac{\text{transmitted frequency maximum deviation}}{\text{multiplier}}$$

## Extra Exam

Antenna gain in dBd vs dBi:

$$\text{gain of antenna in dBd} = \text{gain of antenna in dBi} - 2.15 \text{ dB}$$

Effective radiated power:

$$ERP = \text{transmitter power} * 10^{\left(\frac{\text{gain in dB}}{10}\right)}$$

Length of transmission line:

$$\lambda = \frac{c * \text{velocity factor}}{f}$$

Forward and reflected power:

$$\text{power to load} = \text{forward power} - \text{reflected power}$$

Third-order intermodulation products:

Formula	Formula Solve for $f_2$
$f_i = 2f_1 + f_2$	$f_2 = f_i - 2f_1$
$f_i = 2f_1 - f_2$	$f_2 = 2f_1 - f_i$
$f_i = 2f_2 + f_1$	$f_2 = \frac{f_i - f_1}{2}$
$f_i = 2f_2 - f_1$	$f_2 = \frac{f_i + f_1}{2}$

Operational amplifiers:

$$V_{OUT} = -V_{IN} * \frac{R_F}{R_1}$$

$$A_V = \frac{R_F}{R_1}$$

Image response frequencies:

$$f_{img1} = f_{RF} - 2 * f_{IF}$$

$$f_{img2} = f_{RF} + 2 * f_{IF}$$

Noise floor:

$$BNF = NF + 10 * \log(BW)$$

where:

*BNF* is the bandwidth noise floor (the noise for the entire received bandwidth) (in dBm)

*NF* is the 1-Hz noise floor (in dBm/Hz)

*BW* is the receive filter bandwidth (in Hz)

**Time constant (all components in parallel):**

$$R_t = \frac{R_i}{n} \qquad C_t = C_1 + C_2 \qquad T = R * C$$

**Parts per million:**

$$\text{maximum error} = \text{measurement} * \text{accuracy}$$

**Resonant frequency:**

$$f_R = \frac{1000}{2\pi * \sqrt{LC}}$$

where:

$L$  in  $\mu H$

$C$  in  $pF$

$f_R$  in  $MHz$

**Half-power bandwidth:**

$$\text{half-power bandwidth} = \frac{f_R}{Q}$$

**Transformer turns #1:**

$$N = 100 \times \sqrt{\frac{L}{A_L}}$$

where:

$L$  in  $\mu H$

$A_L$  in  $\mu H/100$  turns

**Transformer turns #2:**

$$N = 1000 \times \sqrt{\frac{L}{A_L}}$$

where:

$L$  in  $mH$

$A_L$  in  $mH/1000$  turns

**Frequency modulation:**

$$\text{deviation ratio} = \frac{D_{MAX}}{M_{MAX}} \qquad \text{modulation index} = \frac{\text{frequency deviation}}{\text{modulating frequency}}$$

**Inductive and capacitive reactances:**

$$X_L = 2\pi fL \qquad X_C = \frac{1}{2\pi fC} \qquad X = X_L - X_C$$

**Phase angle:**

$$\theta = \arctan\left(\frac{X}{R}\right)$$

**Power factor:**

$$\text{power factor} = \cos(\theta) \qquad \text{apparent power} = V_{RMS} * I$$

$$\text{true power} = \text{apparent power} * \text{power factor} \qquad P = I^2 * R$$